

## EM8775

### Wireless Indoor Siren (suited for the EM8710 Wireless GSM Alarm System)

With flashlight and loud signal

- Wireless Indoor Siren suited for the EM8710 Wireless GSM Alarm System
- Works via the long range 868MHz frequency
- Loud siren and strobe flashlight
- Integrated wall mount and tamper alert
- Powered by four LR14 batteries (included)
- Low battery warning

#### DESCRIPTION

The EM8775 Wireless Indoor Siren is suitable for use with the Eminent EM8710 GSM Alarm System. In case of an alarm a loud siren will sound and the strobe flashlight will be visible. The siren is working via the 868MHz frequency and is powered by four LR14 batteries.

#### TECHNICAL

- Function: Indoor siren
- Dimensions in mm. (WxHxD): 90 x 155 x 49
- Weight in grams: 189gr
- Power: 6V (1.5V LR14 size x 4)
- Power Adapter (optional): 6V DC/600mA
- Stand-by current:
- Alarm current:
- Wireless reach: 70 meters (open field)
- Frequency sensors: 868MHz
- Siren Volume: min. 100dBA @ 30cm
- Temperature: -10 to 50 degrees Celsius
- Humidity:

#### LOGISTIC

- Product Weight:
- Retail packaging Dimension (mm):
- Retail packaging Weight:
- Master carton Qty:
- Master carton Dimension (cm):
- Master carton Weight:

