

## EW3945

### Line Interactive UPS 700 VA 390W - with earthed socket

Protect your computer and files with this Uninterruptible Power Supply!

- Line Interactive UPS 700VA with a backup time of approximately 10 minutes @ 120W load
- Sound alarm and LED notification during power failure, with status LEDs
- 6x earthed output sockets EU socket type F with surge protection of which 3x output sockets are equipped with a backup battery
- Input: 1x IEC C14 with detachable cable
- Surge, short circuit, discharge, overcharge and overload protection
- Suitable for wall mounting
- AVR function to stabilize the output voltage

#### DESCRIPTION

Protect your computer and valuable files against power failures and surges with the EW3945 Line Interactive UPS 700 VA with AVR. The UPS is equipped with 6 output sockets. The UPS notifies you with a sound alarm and LED notification during a power failure. It provides you with approximately 10 extra minutes @ 120W load to save your files and to shut down your computer safely. The EW3945 has surge, short circuit, discharge, overcharge and overload protection. The UPS can be mounted on the wall.

Backup power of approx. 10 minutes @ 120 W load

The EW3945 Line Interactive UPS 700 VA has 6 earthed power sockets to protect your computer and valuable files against power failures and surges. Three output sockets are equipped with a backup battery and surge protection. The other three output sockets have surge protection. The built-in battery of the Line Interactive UPS allows you to save your files within approximately 10 minutes @ 120 W load. The output voltage will remain stable thanks to the AVR function. Sound and LED notification during power failure

The UPS notifies you with a sound alarm and LED notification during a power failure. The UPS also notifies you when the built-in battery is running out of power. The built-in status LEDs are showing you the status. The EW3945 has surge, short circuit, discharge, overcharge and overload protection. Easy to connect

It is very easy to connect a computer or another powered device to the EW3945. Just put the power plug of the computer or other device in the power socket of the EW3945. The Line Interactive UPS can be mounted on the wall and has a detachable cable.

#### TECHNICAL

- Output Power: 700 VA 390W
- Input: 230 V~50/60 Hz
- Output: 230 V~50/60 Hz
- Technology: Line Interactive
- Inverter Waveform: Simulated Sine wave
- Voltage stabilization: AVR (Automatic Voltage Regulation)
- Battery: 1 x 12 V / 7 Ah
- Backup time: Approx. 10 minutes for @ 120 W load
- Transfer time: less than 2-6 milliseconds
- Input socket: 1x IEC C14
- Outlet socket: 6x EU socket type F female
- Alarm function: AC fails, Low battery, Overload, Fault
- Protection: Short circuit, discharge, overcharge and overload
- Surge protection: 125 joules
- Control Panel: LED
- Wall mount: Yes
- Weight: 4,5 Kg
- Dimension LxWxH: 280 x 95 x 185 mm
- Power usage stand-alone: 9,5 W
- Equipped with: power cable, 1x spare fuse

- Environment: 0-90 % RH @ 0-40 °C (non-condensing)
- Colour: Black
- Replaceable Battery: Yes



(m  
40

n):  
kg

